

## **OmniFIX HS high screen AES/EBU multicore** n x 2 x 0.22 mm<sup>2</sup> - FRNC

- 0.22 mm<sup>2</sup> conductor cross section (AWG 24)
- double shielding (pair and overall Al foil)
- AL/PETP foil bonded to pair jacket for fast assembly
- flame retardant and non corrosive (FRNC)
- CPR class Eca acc. to EN50575

FRNC





Foil-shielded pairs + a double overall shield (foil + very dense briad) provide maximum shielding. The triple shielding and fulfillment of the flame test on bunched cables according to category C make this Omnifix multicore for installations a sure thing in two ways. Interference free, low-loss signal transfer and safety in case of fire by selected LSZH materials for pair and outer jacket, which emit in case of fire, no toxic and halogen-containing gases and very little smoke. The foil shields and pair jackets are bonded to each other and can be processed very quickly.

## design

cond. construction cond. cross section insulation pair shielding pair jacket overall shield

stranded tinned copper, 7 x 0.20 mm 0.22 mm<sup>2</sup>

Foam-Skin PE, red & blue

stranded tinned copper drain wire + AL/PET foil LSZH (low smoke zero halogen) numbered, grey AL/PET foil + tinned stranded drain wire + tinned copper braid (coverage 85%)

digital audio

outer jacket

## mechanics

min. bending radius working temperature flame retardancy halogen-free

10x overall diameter -30°C / +70°C

acc. to IEC 60332-1-2 and IEC60332-3-24

acc. to IEC 60754-2

## electric

conductor resistance < 85 Ω/km capacitance cond./cond. 43 pF/m characteristic impedance 110 Ω nom. attenuation [dB/100m] 1 MHz 2.3 3.8 5.3 3 MHz 6 MHz 10 MHz 6.6 crosstalk attenuation

15 kHz > 100 dB 10 MHz > 80 dB insulation resistance > 30 G $\Omega$  x km test voltage

cond./cond.

1200 V cond./shield 500 V

order code	no. of pairs	outer Ø mm	heat of combustion kWh/km	cable color	weight kg/m
0X22GH02	2	10.8	640	grey	0.16
0X22GH08	8	16.4	1510	grey	0.37
0X22GH12	12	20.4	2140	grey	0.52
0X22GH16	16	22.8	2740	grey	0.65

technical specifications are subject to change

